

60W/80W Power Kit

Appurtenance

- 1 60W AC Adapter
- 2 80W AC Adapter
- 3 DC Board
- 4 DC Jack Cable
- 5 ATX Cable
- 6 Power Cord

| | | Specification | | | | | | | | |
|--------------------------|------|-----------------|-----------------|------|------|------|-------|-----|------|------|
| Model No . | | PDB060R | PDB080R | | | | | | | |
| Input DC Voltage Require | | 11.4 V ~ 12.6 V | 11.4 V ~ 12.6 V | | | | | | | |
| DC Board Maximum Output | | 80.2 W | 80.2 W | | | | | | | |
| AC Adapter | | 60W | 80W | | | | | | | |
| Operating Temperature | | 0~45°C | 0~45°C | | | | | | | |
| Maximum Output (W) | | | | | | | | | | |
| Output Voltage (V) | 5VSB | +3.3V | +5V | +12V | -12V | 5VSB | +3.3V | +5V | +12V | -12V |
| Output Current (A) | 1.5 | 5 | 5 | 2.5 | 0.1 | 1.5 | 5 | 5 | 2.5 | 0.1 |
| Power Output (W) | 7.5 | 16.5 | 25 | 30 | 1.2 | 7.5 | 16.5 | 25 | 30 | 1.2 |

54.95 EUR
incl. 19% VAT, plus [shipping](#)

Model No.: PDB060R
 Input DC Voltage Require: 11.4 V ~ 12.6 V
 Maximum Output: 80.2 W
 Operating Temperature: 0 ~ 45 C

Maximum Output (W):
 Output Voltage (V) 5VSB +3.3V +5V +12V -12V
 Output Current (A) 1.50 5.00 5.00 2.50 0.10
 Power Output (W) 7.50 16.50 25.00 30.00 1.20

- Include Parts:
- Part 1 80W D2D Board
 - Part 2 60W Adapter
 - Part 3 DC Jack Power Cable
 - Part 4 ATX Power Cable
 - Part 5 AC Power Cable
 - Part 6 Screw Bag